

CLAIMS

What is claimed is:

- 1        1. A method comprising:  
2        computing a complex phase difference between a current symbol and a previous  
3        symbol;  
4        separating a real value component (R) from a corresponding imaginary value  
5        component (I) forming the complex phase difference;  
6        determining at least one boundary constraint line of a complex phase map for a  
7        selected demodulation scheme; and  
8        computing an arithmetic combination of the real value component and the  
9        corresponding imaginary value component to detect whether a series of bits falls within  
10       a selected region of the complex phase map defined by the at least one boundary  
11       constraint line.
- 1        2. The method of claim 1, wherein the previous symbol is received by a  
2        demodulator determining the complex phase difference prior to the current symbol.
- 1        3. The method of claim 2, wherein the previous symbol is received  
2        immediately prior to the current symbol.
- 1        4. The method of claim 1, wherein the at least one boundary constraint line  
2        for the complex phase map associated with a Quaternary Phase Shift Keying (QPSK)  
3        demodulation scheme includes a first boundary constraint line being equivalent to  $R+I$   
4         $=0$  and a second boundary constraint line being equivalent to  $R-I = 0$ .
- 1        5. The method of claim 1, wherein the at least one boundary constraint line  
2        for the complex phase map associated with a Binary Phase Shift Keying (BPSK)  
3        modulation scheme include a boundary constraint line being equivalent to  $I = 0$ .
- 1        6. The method of claim 1, wherein the detection of the series of bits  
2        includes detecting a sign bit of the arithmetic combination being a signed 2's  
3        complement combination of an addition of the real value component and the imaginary  
4        value component.

1           7.     The method of claim 6, wherein the detection of the series of bits further  
2 includes detecting a sign bit of a bitwise inversion of a signed 2's complement  
3 combination of a subtraction of the imaginary value component from the real value  
4 component.

1           8.     The method of claim 1, wherein the detection of the series of bits  
2 includes detecting a sign bit of the real value component of the complex phase  
3 difference.

1           9.     The method of claim 1 further comprising performing a channel  
2 estimation operation on a carrier propagating a plurality of symbols, including the  
3 current symbol and the previous symbol, by counting a number of symbols that fall  
4 within an estimated area of the complex phase map, the estimated area being bounded  
5 by boundary constraint lines based on a parameterized real value component.

1           10.    The method of claim 9 further comprising:  
2 determining that the carrier is reliable if the number of symbols that fall within  
3 the estimated area is greater than a threshold value.

1           11.    A method comprising:  
2 determining a complex phase difference between a current symbol and a  
3 complex frequency representation operating as a reference symbol;  
4 separating a real value component (R) from a corresponding imaginary value  
5 component (I) forming the complex phase difference;  
6 determining at least one boundary constraint line of a complex phase map for a  
7 selected demodulation scheme; and  
8 detecting a first series of bits if an arithmetic combination of the real value  
9 component and the corresponding imaginary value component falls within a first  
10 selected region of the complex phase map defined by the at least one boundary  
11 constraint line.

1           12.    The method of claim 11, wherein the detecting of the first series of bits  
2 includes detecting a sign bit of the arithmetic combination being a signed 2's

3 complement combination of an addition of the real value component and the imaginary  
4 value component.

1 13. The method of claim 12, wherein the detecting of the first series of bits  
2 further includes detecting a sign bit of a bitwise inversion of a signed 2's complement  
3 combination of a subtraction of the imaginary value component from the real value  
4 component.

1 14. The method of claim 11, wherein the detecting of the first series of bits  
2 includes detecting a sign bit of the real value component of the complex phase  
3 difference.

1 15. A demodulator comprising:  
2 a logic unit to separate a real value component (R) from a corresponding  
3 imaginary value component (I) forming a complex phase difference between two  
4 symbols;  
5 a Quaternary Phase Shift Keying (QPSK) demodulator unit to receive the real  
6 value component and the imaginary value component from the logic unit and to detect  
7 at least two bit values;  
8 a Binary Phase Shift Keying (BPSK) demodulator unit to receive the real value  
9 component from the logic unit and to detect a bit value being equivalent to a sign bit of  
10 the real value component;  
11 a first select unit coupled to both the QPSK demodulator unit and the BPSK  
12 demodulator unit, the first select unit to select one of the QPSK demodulator unit and  
13 the BPSK demodulator unit to perform demodulation;  
14 a second select unit coupled to the first select unit, the QPSK demodulator unit  
15 and the BPSK demodulator unit, the second select unit to route either an output of the  
16 QPSK demodulator unit or an output of the BPSK demodulator unit based on an output  
17 from the first select unit.

1 16. A method comprising:  
2 separating a real value component (R) from a corresponding imaginary value  
3 component (I) forming a complex phase difference between two symbols provided over  
4 a carrier;

5 computing at least one parameterized real value component (aR) by multiplying  
6 the real value component (R) with a parameter (a);

7 for a plurality of symbols, counting a number of symbols that fall within an  
8 estimated area of a complex phase map associated with a selected demodulation  
9 scheme, the estimated area is bounded by boundary constraint lines based on the  
10 parameterized real value component; and

11 determining that the carrier is reliable if the number of symbols that fall within  
12 the estimated area is greater than a threshold value.

1 17. The method of claim 16 further comprising:

2 determining that the carrier is unreliable if the number of symbols that fall  
3 within the estimated area is less than the threshold value.

1 18. The method of claim 16, wherein the boundary constraint lines are  
2 equivalent to  $aR+I=0$  and  $aR-I=0$ .

1 19. The method of claim 16, wherein the boundary constraint lines are  
2 equivalent to (i)  $aR+I=0$ , (ii)  $aR-I=0$ , (iii)  $-R/a-I=0$ , and (iv)  $-R/a+I=0$ .

1 ~~20.~~ A software module stored in a machine readable medium and executed  
2 by a processor, comprising:

3 a first software module to separate a real value component (R) from a  
4 corresponding imaginary value component (I) forming a complex phase difference  
5 between multiple symbols provided over a carrier;

6 a second software module to compute at least one parameterized real value  
7 component (aR) by multiplying the real value component (R) with a parameter (a);

8 a third software module to count a number of symbols that fall within an  
9 estimated area of a complex phase map associated with a selected demodulation  
10 scheme, the estimated area is bounded by boundary constraint lines based on the  
11 parameterized real value component; and

12 a fourth software module to determine that the carrier is reliable if the number  
13 of symbols that fall within the estimated area is greater than a threshold value and that  
14 the carrier is unreliable if the number of symbols that fall within the estimated area is  
15 less than the threshold value.

Al Conth

7  
Add Al

1947	1948	1949	1950	1951	1952	1953	1954	1955	1956	1957	1958	1959	1960	1961	1962	1963	1964	1965	1966	1967	1968	1969	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355</
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	--------